KINGSTON™

NOW FEATURING SMARTKEY™

KINGSTON™ LEVER

A SMART SOLUTION
FOR LIGHT COMMERCIAL APPLICATIONS

- Add Security with Key Control
- ADA Approved in all Functions
- ANSI/BHMA Grade 2
- Now on the Reversible Lever Chassis
  - Easy Installation
  - New Chassis with Improved Durability
  - Concealed Screws
- New SmartKey™ Cylinder—Re-Key in Seconds
- Traditional Pin & Tumbler Cylinder Available

Kwikset®
The Beauty of Strength.

A SMART SOLUTION FOR MULTIFAMILY HOUSING

INCREASE EFFICIENCY | SAVE TIME & MONEY | ADD SECURITY WITH KEY CONTROL

Kingston™ Lever

Specifications:

Door Prep	Crossbore 2-1/8" Edge Bore 1" Latch Face 1" x 2-1/4" Optional: 1-1/8" x 2-1/4" UL.
Backset	Adjustable to 2-3/8" or 2-3/4" UL 2-3/4" standard, 2-3/8" optional.
Door Thickness	1-3/8" – 1-3/4" doors standard. 2-1/4" optional passage and entry functions.
Cylinder	Pin & Tumbler or SmartKey cylinder.
Faceplates	1" x 2-1/4". Specify round corner, square or drive-in. UL 1-1/8" square optional.
Latches	Adjustable to 2-3/8" or 2-3/4". Specify RCAL, SCAL or RFAL.
Strikes	2-1/4" full lip. Specify round corner or square corner. Other options available. UL options include 2-3/4" T-Strike and 4-7/8" ASA.
Door Handing	Reversible for right or left-hand doors.
ANSI/BHMA	Non-handed. A156.2 Grade 2.
ADA	Lever functions satisfy 4.13.9 ADA requirements.
UL	Meets 3 hour fire rating for all UL functions.

Functions:

Passage/Hall/Closet: Both levers always free.



Privacy/Bed/Bath: Both levers locked or unlocked by turnbutton inside. Outside lever unlocked by emergency key.



Keyed Entry Lever: Both sides locked or unlocked by key outside or turnbutton inside.



Free interior: Exterior always locked and interior always unlocked.



Half Dummy Trim, Surface Mounted: For doors where only a pull is required. No operation.

Dimensions:



Design	A	B	C	C *(Keyed)*
Kingston™	2 5/8"	4 7/32"	2 7/16"	2 7/8"

SMARTKEY™ featuring BumpGuard™:

RE-KEY IN THREE EASY STEPS

Insert functioning key and turn 1/4 turn clockwise.

Insert and remove the SmartKey learn tool. Remove functioning key.

Insert new key and turn 1/2 turn counter-clockwise. Your lock is now re-keyed!

Finishes:

3 Polished Brass

26D Brushed Chrome

Kwikset

The Beauty of Strength.

19701 DaVinci • Lake Forest, CA 92610 • www.kwikset.com • 1-800-327-LOCK

LIT 7-1-92 11/08 14837

© 2008 Kwikset Corporation, Lake Forest, CA 92610