



# Introducing PHOENIX<sup>®</sup>

- Proven Traditional Style
- Features **SMARTKEY** Re-key Technology
- ANSI/BHMA Grade 2 Certified Quality & Security
- Features KwikInstall™ for Easy Installation





**Kwikset**  
*Signature Series*

# PHOENIX<sup>®</sup>

## Specifications:

<b>Door Prep</b>	Cross Bore 2 1/8". Edge Bore 1". Latch face 1" x 2 1/4"
<b>Backset</b>	Adjustable to 2 3/8" or 2 3/4"
<b>Door Thickness</b>	1 3/8" - 1 3/4" doors standard
<b>Cylinder</b>	SmartKey <sup>®</sup>
<b>Faceplates</b>	1" x 2 1/4". Specify round corner, square corner. Other options available.
<b>Strikes</b>	2 1/4" full lip standard. Specify round corner, square corner. Other options available.
<b>Bolt</b>	1/2" throw for all functions.
<b>Door Handing</b>	Reversible for right or left-handed doors.
<b>ANSI/BHMA</b>	A156.2 Grade 2

## Functions:

	<b>Passage/Hall/Closet:</b> Both knobs always free.
	<b>Privacy/Bed/Bath:</b> Both knobs locked or unlocked by turnbutton inside. Outside knob unlocked by emergency key.
	<b>Keyed Entry:</b> Both sides locked or unlocked by key outside or turnbutton inside.
	<b>Half Dummy Trim, Surface Mounted:</b> For doors where only a pull is required. No operation.

## SMARTKEY<sup>®</sup> featuring BumpGuard<sup>™</sup>:

### EASILY RE-KEY IN THREE EASY STEPS




1  
Insert functioning key and turn 1/4 turn clockwise.

2  
Insert and remove the SmartKey learn tool. Remove functioning key.

3  
Insert new key and turn 1/2 turn counter-clockwise. Your lock is now re-keyed!

## Dimensions:



Design	A	B	C
Phoenix <sup>®</sup>	2 5/8"	2 1/4"	2 3/16"

## Finishes:



Antique Brass (5)

Satin Nickel (15)

Venetian Bronze (11P)

Satin Chrome (26D)

Polished Brass (3)